

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
2430	SYS1	2.21+	27256	U680	160-2551-05	BD38	1	A1	01	Must have WFM ROM's v2.0 (-02)
2430	SYS1	2.21+	27256	U682	160-2552-05	1B5B	2	A1	01	
2430	SYS1	2.21+	27256	U690	160-2553-05	7233	3	A1	01	
2430	SYS1	2.21+	27256	U692	160-2554-05	4577	4	A1	01	
2430	SYS2	2.21+	27128A	U670	160-2555-05	A1CE	1	A2	01	
2430A	SYS1	1.90+	27128A	U670	160-4398-07	C307	1	B1	01	Must have WFM ROM's 1.4
2430A	SYS2	1.90+	27512	U680	160-4399-07	6470	1	B2	01	
2430A	SYS2	1.90+	27512	U682	160-4400-07	ED8B	2	B2	01	
2430A	SYS2	1.90+	27512	U690	160-4401-07	6673	3	B2	01	
2430A	SYS2	1.90+	27512	U692	160-4402-07	8ECF	4	B2	01	
2430A	SYS1	2.31-*	27128A	U670	160-6491-03	43E5	1	C1	01	Must have WFM ROM's 2.5 + possibly mod
2430A	SYS2	2.31-*	27512	U680	160-6492-03	3F66	1	C2	01	
2430A	SYS2	2.31-*	27512	U682	160-6493-03	C4FF	2	C2	01	
2430A	SYS2	2.31-*	27512	U690	160-6494-03	AAF4	3	C2	01	
2430A	SYS2	2.31-*	27512	U692	160-6495-03	0430	4	C2	01	
2432	SYS1	1.52	27128A	U670	160-4175-02	FEC6	1	D1	01	
2432	SYS2	1.52	27512	U680	160-4176-02	BFE9	1	D2	01	
2432	SYS2	1.52	27512	U682	160-4177-02	2F4E	2	D2	01	
2432	SYS2	1.52	27512	U690	160-4178-02	0411	3	D2	01	
2432	SYS2	1.52	27512	U692	160-4179-02	9A47	4	D2	01	
2432A	SYS1	1.13	27128A	U670	160-5903-01	DCB2	1	E1	01	
2432A	SYS2	1.13	27512	U680	160-5904-01	9452	1	E2	01	
2432A	SYS2	1.13	27512	U682	160-5905-01	5C6B	2	E2	01	
2432A	SYS2	1.13	27512	U690	160-5906-01	516F	3	E2	01	
2432A	SYS2	1.13	27512	U692	160-5907-01	B537	4	E2	01	
2432A	SYS1	2.30-	27128A	U670	160-5903-05	7D7D	1	J1	01	Must have WFM 2.5 + possibly mod
2432A	SYS2	2.30-	27512	U680	160-5904-05	AFE2	1	J2	01	
2432A	SYS2	2.30-	27512	U682	160-5905-05	B894	2	J2	01	
2432A	SYS2	2.30-	27512	U690	160-5906-05	D918	3	J2	01	
2432A	SYS2	2.30-	27512	U692	160-5907-05	4319	4	J2	01	
2440	SYS1	1.92	27128A	U670	160-4992-03	09B5	1	F1	01	
2440	SYS2	1.92	27512	U680	160-4993-03	1B0D	1	F2	01	
2440	SYS2	1.92	27512	U682	160-4994-03	C10D	2	F2	01	
2440	SYS2	1.92	27512	U690	160-4995-03	5030	3	F2	01	
2440	SYS2	1.92	27512	U692	160-4996-03	CCC7	4	F2	01	
2440	SYS1	2.30-*	27128A	U670	160-4941-07	928C	1	G1	01	Must have WFM 2.5 + possibly mod
2440	SYS2	2.30-*	27512	U680	160-4942-07	546F	1	G2	01	
2440	SYS2	2.30-*	27512	U682	160-4943-07	87BE	2	G2	01	
2440	SYS2	2.30-*	27512	U690	160-4944-07	16B6	3	G2	01	
2440	SYS2	2.30-*	27512	U692	160-4945-07	3FF9	4	G2	01	
2431L	SYS1	2.24	27128A	U670	160-6705-01	D531	1	H1	01	
2431L	SYS2	2.24	27C512	U680	160-6706-01	3C52	1	H2	01	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
2431L	SYS2	2.24	27C512	U682	160-6707-01	FC05	2	H2	01	
2431L	SYS2	2.24	27C512	U690	160-6708-01	AE5D	3	H2	01	
2431L	SYS2	2.24	27C512	U692	160-6709-01	43D8	4	H2	01	
2431L	SYS1	2.30-*	27128A	U670	160-6705-02	0B5F	1	I1	01	Must have WFM 2.5 + possibly mod
2431L	SYS2	2.30-*	27C512	U680	160-6706-02	3337	1	I2	01	
2431L	SYS2	2.30-*	27C512	U682	160-6707-02	4C6B	2	I2	01	
2431L	SYS2	2.30-*	27C512	U690	160-6708-02	4902	3	I2	01	
2431L	SYS2	2.30-*	27C512	U692	160-6709-02	8E21	4	I2	01	
DC510										Use DC5010
PS5010	SYS	1.0	2732A	U1201	160-1331-00	D347	1	A	02	
PS5010	SYS	1.0	2732A	U1200	160-1332-00	F0B6	2	A	02	
PS5010	SYS	1.0	2732A	U1101	160-1333-00	1400	3	A	02	
PS5010	SYS	1.0	2732A	U1100	160-1334-00	4C39	4	A	02	
DC5010	SYS	1.2+	2732A		160-1111-02	947A	1	B1	02	
DC5010	GPIB	1.2+	2732A		160-1091-01	F1D6	1	B1	02	
DC5010	GPIB	1.2+	2732A		160-1092-01	7349	2	B1	02	
DM5120	SYS	1.0	27C256		5120-800	0BBD	1	C	02	
PFG5105	SYS	1.1	27256		050-1233	D011	1	D	02	
SI5010	SYS		2716	U1011	160-1482-00	342E	1	E1	02	
SI5010	SYS		2732A	U1103	160-1483-00	468A	1	E2	02	
SI5010	SYS		2732A	U1200	160-1484-01	D5DF	2	E2	02	
AA5001	SYS		2764		160-2000-00	432C	1	F	02	
SG5030	SYS				160-6447-02	D2FB	1	G	02	
SG5030	SYS				160-6448-02	0CC4	2	G	02	
AFG5102	SYS	0.8	27C256	U105	050-8211-07	9212	1	H	02	
FG5010	SYS		2716		160-1712-01	5B8D	1	I1	02	Not EPROM
FG5010	SYS		82S107		160-1713-01				02	
DM5110	SYS		27C256-15		160-6238-00	D9FC	1	J	02	
SG5010	SYS	1.1	27128	U4050	160-1802-01	2322	1	K	02	
SG5010	SYS	1.1	27128	U4060	160-1803-01	1F52	2	K	02	
AT5010	SYS	1.12	27C256		160-6580-00	83A4	1	L	02	
DC5009	SYS	1.2	2732A		160-1076-02	432D	1	M1	02	
DC5009	GPIB	1.2	2732A		160-1091-02	F1D6	1	M2	02	
DC5009	GPIB	1.2	2732A		160-1092-02	7349	2	M2	02	
CG5010	SYS		27C256		160-6849-00	37CD	1	N	02	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
SI5020	SYS	1.11	27C256		160-6758-00	93AE	1	O	02	
DM5010	SYS	1.0	2732A		160-1326-00	65DA	1	P	02	
DM5010	SYS	1.0	2732A		160-1327-00	99A6	2	P	02	
DM5010	SYS	1.0	2732A		160-1328-00	C9C2	3	P	02	
DM5010	SYS	1.0	2732A		160-1329-00	209C	4	P	02	
									02	
PS5004	SYS	1.0	27C128	U3040	160-2144-00	57A6	1	Q	02	
AFG5101	SYS	1.4	27C256	U105	050-1201-04	C1D8	1	R	02	
PG5110	SYS	1.0	27C256	U104	050-6220-10	42A6	1	S	02	
PG5110	SYS	1.0	27C256	U105	050-6221-10	EDA6	2	S	02	
PG5110	SYS	1.0	27C256	U106	050-6222-10	2434	3	S	02	
2246A	SYS	*	27010	U2519	160-5063-02	3AA0	1	A	03	
2245A	SYS		27010	U2519	160-5064-04	4EC4	1	B	03	
2245A	SYS	-	27010	U2519	160-6500-00	D1EE	1	C	03	
2247A	SYS	*	27010	U2519	160-5663-01	F6F2	1	D	03	
2245	SYS		27512	U2519	160-4293-01	47C1	1	E	03	
2246	SYS	*-	27512	U2519	160-4082-02	4774	1	F1	03	
2246	SYS	*-	27256	U2520	160-4083-02	4ADA	1	F2	03	
2252	SYS	-	27C010	U2532	160-7242-02	60EC	1	G	03	
2252	SYS	-	27C010	U2531	160-7243-02	5DDF	2	G	03	
2252	SYS	-	27C010	U2519	160-7244-02	17A3	3	G	03	
2247A	SYS	*	27010		160-5663-02	3357	1	H	03	
2247A	SYS	+	27010	U2519	160-5663-03	3357	1	I	03	
2247A	SYS	+	27010	U2519	160-6502-03	3357	1	J	03	B020100 - up
11201A										Use 11402A
11203										Use 11402A
11403										Use 11402A
11403A										Use 11402A
CSA404										Use 11402A
11401	A7 DSY	4.0	27512	U602	160-3716-07	18CD	1	A1	04	Display
11401	A7 DSY	4.0	27512	U612	160-3717-07	9E85	2	A1	04	Display

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
11401	A6 TB	4.2	27512	U281	160-3941-08	82A9	3	A1	04	Digitizer
11401	A6 TB	4.2	27512	U283	160-3942-08	9A64	4	A1	04	Digitizer
11401	A18 EXE	4.2	27512	U630	160-3740-10	EE03	1	A2	04	Executive
11401	A18 MEM	4.2	27512	U730	160-3741-10	117D	2	A2	04	Executive
11401	A18 MEM	4.2	27512	U620	160-3742-10	C0B5	3	A2	04	Executive
11401	A18 MEM	4.2	27512	U720	160-3743-10	641C	4	A2	04	Executive
11401	A18 MEM	4.2	27512	U612	160-3744-10	4AC4	5	A2	04	Executive
11401	A18 MEM	4.2	27512	U712	160-3745-10	C6A7	6	A2	04	Executive
11401	A18 MEM	4.2	27512	U600	160-3746-10	DAF6	7	A2	04	Executive
11401	A18 MEM	4.2	27512	U700	160-3747-10	63C1	8	A2	04	Executive
11401	A17 CPU	4.2	27512	U250	160-3748-11	69CE	1	A3	04	Executive, 11401 only
11401	A17 CPU	4.2	27512	U240	160-3749-11	4718	2	A3	04	Executive, 11401 only
11402	A7 DSY	4.0	27512	U602	160-3716-07	18CD	1	B1	04	Display
11402	A7 DSY	4.0	27512	U612	160-3717-07	9E85	2	B1	04	Display
11402	A6 TB	4.2	27512	U281	160-3941-08	82A9	3	B1	04	Digitizer
11402	A6 TB	4.2	27512	U283	160-3942-08	9A64	4	B1	04	Digitizer
11402	A18 MEM	4.1*	27512	U630	160-3740-09	EE99	1	B2	04	Executive
11402	A18 MEM	4.1*	27512	U730	160-3741-09	117D	2	B2	04	Executive
11402	A18 MEM	4.1*	27512	U620	160-3742-09	C0B5	3	B2	04	Executive
11402	A18 MEM	4.1*	27512	U720	160-3743-09	641C	4	B2	04	Executive
11402	A18 MEM	4.1*	27512	U612	160-3744-09	4AC4	5	B2	04	Executive
11402	A18 MEM	4.1*	27512	U712	160-3745-09	C6A7	6	B2	04	Executive
11402	A18 MEM	4.1*	27512	U600	160-3746-09	DAF6	7	B2	04	Executive
11402	A18 MEM	4.1*	27512	U700	160-3747-09	63C1	8	B2	04	Executive
11402	A17 CPU	4.1*	27512	U250	160-4554-09	7814	1	B3	04	Executive, 11402 only
11402	A17 CPU	4.1*	27512	U240	160-4555-09	4042	2	B3	04	Executive, 11402 only
11403	A18 MEM	2.2*	27C010	U820	160-6119-01	3B1A	1	C1	04	Executive
11403	A18 MEM	2.2*	27C010	U920	160-6120-01	095E	2	C1	04	Executive
11403	A18 MEM	2.2*	27C010	U810	160-6121-01	108B	3	C1	04	Executive
11403	A18 MEM	2.2*	27C010	U910	160-6122-01	021E	4	C1	04	Executive
11403	A18 MEM	2.2*	27C010	U800	160-6123-01	8FA2	5	C1	04	Executive
11403	A18 MEM	2.2*	27C010	U900	160-6124-01	6638	6	C1	04	Executive
11403	A18 MEM	2.2*	27C010	U830	160-6621-01	8FBF	7	C1	04	Executive
11403	A18 MEM	2.2*	27C010	U930	160-6622-01	EC02	8	C1	04	Executive
11403	A15 MMU	2.0*	27C512	U140	160-6125-01	709D	1	C2	04	Display
11403	A15 MMU	2.0*	27C512	U150	160-6126-01	0BD5	2	C2	04	Display
11403	A6 TB		27C512	U281	160-6552-02	C1B8	3	C2	04	Digitizer
11403	A6 TB		27C512	U283	160-6553-02	729E	4	C2	04	Digitizer
11402A	A18 MEM	3.3*	27C010	U820	160-6119-11	747F	1	D1	04	Executive
11402A	A18 MEM	3.3*	27C010	U920	160-6120-11	EBAD	2	D1	04	Executive
11402A	A18 MEM	3.3*	27C010	U810	160-6121-11	BD17	3	D1	04	Executive
11402A	A18 MEM	3.3*	27C010	U910	160-6122-11	7FF4	4	D1	04	Executive
11402A	A18 MEM	3.3*	27C010	U800	160-6123-11	776D	5	D1	04	Executive
11402A	A18 MEM	3.3*	27C010	U900	160-6124-11	3F4C	6	D1	04	Executive
11402A	A18 MEM	3.3*	27C010	U830	160-6621-11	0835	7	D1	04	Executive
11402A	A18 MEM	3.3*	27C010	U930	160-6622-11	7B63	8	D1	04	Executive
11402A	A6 TB	3.0*	27C512	U281	160-6552-10	C147	1	D2	04	Digitizer
11402A	A6 TB	3.0*	27C512	U283	160-6553-10	7261	2	D2	04	Digitizer

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
11402A	A15 MMU	3.10*	27C512	U140	160-6976-10	6C4F	3	D2	04	Display
11402A	A15 MMU	3.10*	27C512	U150	160-6977-10	C54E	4	D2	04	Display
2445										Use 2465
2455										Use 2465
2445A										Use 2465A
2455A										Use 2465A
2467										Use 2465A
2445B										Use 2465B
2467B										Use 2465B
2465	SYS	11-	2764		160-1625-11	59F2	1	A	05	Make sure A5R2532 is 23.7 k
2465	SYS	11-	2764		160-1626-11	0720	2	A	05	
2465	SYS	11-	2764		160-1627-11	06F9	3	A	05	
2465	SYS	11-	2764		160-1628-11	3D5D	4	A	05	
2465	SYS	11-	27128A		160-1994-11	463F	1	B	05	
2465	SYS	11-	27128A		160-1995-11	60F0	2	B	05	
2465			2732		160-1631-02	901B	1	H1	05	
2465	BU	06	2732		160-1833-06	67AB	1	C	05	
2465	TV	02	2764		160-2216-02	A39C	1	D	05	
2465	CT	05*	27256		160-2298-05	750B	1	E	05	
2465	DM	02	27256		160-3299-02	4780	1	F	05	
2465	GP1	15	2764A		160-1681-15	5E28	1	G1	05	
2465	GP2	15	27128A		160-1692-15	DD50	1	G2	05	
2465A	SYS	09+/-	27512	U2160	160-3302-09	38FE	1	H	05	2467 <B011012: remove A1R362 and change A1R669 to 549 ohms
2465A	SYS	09+/-	27512	U2260	160-3303-09	C813	2	H	05	
2465A	R/O		2732		160-1631-02	901B	1	H1	05	
2465A	BU	02+	2732A		160-3676-02	23B8	1	I	05	
2465A	TV	02+	2764A		160-3677-02	8893	1	J	05	
2465A	CT	04*+	27513		160-3678-04	2B48	1	K	05	
2465A	DM	01+			160-3679-01		1	L	05	
2465A	GP1	02*	2732A		160-3674-02	89AB	1	M1	05	
2465A	GP2	02*	27128A		160-3675-02	C045	1	M2	05	
2465B	SYS	09	27C512	U2160	160-5370-09	6758	1	N	05	
2465B	SYS	09	27C512	U2260	160-5371-09	2FE5	2	N	05	
2465B	BU	02	2732A	U4260	160-3676-02	23B8	1	I	05	
2465B	TV						1	O	05	
2465B	CT	01	27513	U5930	160-5376-01	5250	1	P	05	
2465B	DM	01	27256	U5281	160-5372-01	786E	1	Q	05	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
2465B	GP1	03	2764A	U4710	160-5373-03	8008	1	R1	05	
2465B	GP2	03	27256	U4715	160-5374-03	DBB4	1	R2	05	
2465B	SYS	02+	27011	U2360	160-5877-02	AE34	1	S	05	SMD control board
2465B	BU						1	T	05	SMD control board
2465B	TV						1	U	05	SMD control board
2465B	CT	00	27513		160-5880-00	8422	1	V	05	SMD control board
2465B	DM						1	W	05	SMD control board
2465B	GP1	02+	2764A	U4710	160-5881-02	9112	1	X1	05	SMD control board
2465B	GP2	02+	27C256	U4715	160-5882-02	DD04	1	X2	05	SMD control board
2221A										Use 2232
2224										Use 2232
2220	SYS	15	27C512	U9109	160-3975-15	BF27	1	A	06	
2220	SYS	15	27C512	U9110	160-3976-15	903A	2	A	06	
2220	COMM	15	27C512	U1243	160-2998-15	C566	1	B	06	
2221	SYS	15	27C512	U9109	160-4859-15	0739	1	C	06	
2221	SYS	15	27C512	U9119	160-4860-15	E381	2	C	06	
2221	COMM	15	27C512	U1243	160-4864-15	82A6	1	D	06	
2230	SYS	15	27C512	U9110	160-3532-15	9049	1	E	06	
2230	SYS	15	27C512	U9109	160-3633-15	BF95	2	E	06	
2230	COMM	15	27C512	U1243	160-2998-15	C566	1	B	06	
2211	SYS		27C512	U1305	160-6049-01	C6AE	1	F1	06	
2211	COMM		27C256	U1253	160-6055-03	2F29	1	F2	06	
2232	SYS	7	27C010	U9120	160-6188-07	AA2B	1	G	06	
2232	SYS	7	27C010	U9121	160-6192-07	1CA6	2	G	06	
2236	DMM		2716	U1402	160-1808-00	5395	1	H1	06	
2236	DMM		2764	U1401	160-1809-00	819E	1	H2	06	
2212	SYS	1.4	27C010	ODD	160-9144-02	C9A4	1	I	06	
2212	SYS	1.4	27C010	EVEN	160-9145-02	9576	2	I	06	
2212	SYS	2.1	27C010	ODD	160-9144-04	3CF9	1	J	06	
2212	SYS	2.1	27C010	EVEN	160-9145-04	8BB4	2	J	06	
2214	SYS	3	27C512	U1258	160-7285-03	B09F	1	K	06	
468	SYS		AM27C64	U565	160-0459-02	C2AC	1	L1	06	Original device CY7C264, must be used with adapter card
468	SYS		AM27C64	U575	160-0759-02	EF01	1	L2	06	Original device CY7C264, must be used with adapter card
11301	SYS	3.1 ±	27C512	U1330	160-4204-08	CE0D	1	A	07	Direct replacement for v2.5 or higher. Lower must have trig mod installed.
11301	SYS	3.1 ±	27C512	U1430	160-4205-08	2EDB	2	A	07	
11301	SYS	3.1 ±	27C512	U1400	160-4206-08	4745	3	A	07	
11301	SYS	3.1 ±	27C512	U1100	160-4207-08	F551	4	A	07	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
11301	SYS	3.1 ±	27C512	U1200	160-4208-08	DAAE	5	A	07	
11301	SYS	3.1 ±	27C512	U1300	160-4209-08	779C	6	A	07	
11301	SYS	3.1 ±	27C512	U1000	160-4294-08	23C4	7	A	07	
11301	SYS	3.1 ±	27C512	U1230	160-4295-08	C1D4	8	A	07	
11302	SYS	3.1 ±	27C512	U1330	160-4470-08	99C9	1	B	07	
11302	SYS	3.1 ±	27C512	U1430	160-4471-08	6FA6	2	B	07	
11302	SYS	3.1 ±	27C512	U1400	160-4472-08	A048	3	B	07	
11302	SYS	3.1 ±	27C512	U1100	160-4473-08	D521	4	B	07	
11302	SYS	3.1 ±	27C512	U1200	160-4474-08	E545	5	B	07	
11302	SYS	3.1 ±	27C512	U1300	160-4475-08	865F	6	B	07	
11302	SYS	3.1 ±	27C512	U1000	160-4476-08	444B	7	B	07	
11302	SYS	3.1 ±	27C512	U1230	160-4477-08	F734	8	B	07	
11301A	SYS	1.1+	27C512	U1330	160-4204-10	B893	1	C	07	
11301A	SYS	1.1+	27C512	U1430	160-4205-10	2B51	2	C	07	
11301A	SYS	1.1+	27C512	U1400	160-4206-10	E421	3	C	07	
11301A	SYS	1.1+	27C512	U1100	160-4207-10	B0C6	4	C	07	
11301A	SYS	1.1+	27C512	U1200	160-4208-10	D564	5	C	07	
11301A	SYS	1.1+	27C512	U1300	160-4209-10	BC58	6	C	07	
11301A	SYS	1.1+	27C512	U1000	160-4294-10	B496	7	C	07	
11301A	SYS	1.1+	27C512	U1230	160-4295-10	EFB6	8	C	07	
11302A	SYS	1.1+	27C512	U1330	160-4470-60	77F5	1	D	07	
11302A	SYS	1.1+	27C512	U1430	160-4471-60	152E	2	D	07	
11302A	SYS	1.1+	27C512	U1400	160-4472-60	405B	3	D	07	
11302A	SYS	1.1+	27C512	U1100	160-4473-60	51FF	4	D	07	
11302A	SYS	1.1+	27C512	U1200	160-4474-60	095A	5	D	07	
11302A	SYS	1.1+	27C512	U1300	160-4475-60	F8F0	6	D	07	
11302A	SYS	1.1+	27C512	U1000	160-4476-60	9351	7	D	07	
11302A	SYS	1.1+	27C512	U1230	160-4477-60	1D38	8	D	07	
11301	SYS	2.7 *±	27C512	U1330	160-4204-07	6593	1	E	07	Direct replacement for v2.5 or higher. Lower must have trig mod installed.
11301	SYS	2.7 *±	27C512	U1430	160-4205-07	68B4	2	E	07	
11301	SYS	2.7 *±	27C512	U1400	160-4206-07	9F05	3	E	07	
11301	SYS	2.7 *±	27C512	U1100	160-4207-07	6AD0	4	E	07	
11301	SYS	2.7 *±	27C512	U1200	160-4208-07	CC98	5	E	07	
11301	SYS	2.7 *±	27C512	U1300	160-4209-07	02CE	6	E	07	
11301	SYS	2.7 *±	27C512	U1000	160-4294-07	D50C	7	E	07	
11301	SYS	2.7 *±	27C512	U1230	160-4295-07	FF61	8	E	07	
11301	SYS	2.2 *+	27C512	U1330	160-4204-03	978F	1	F	07	
11301	SYS	2.2 *+	27C512	U1430	160-4205-03	A541	2	F	07	
11301	SYS	2.2 *+	27C512	U1400	160-4206-03	3C3E	3	F	07	
11301	SYS	2.2 *+	27C512	U1100	160-4207-03	44D5	4	F	07	
11301	SYS	2.2 *+	27C512	U1200	160-4208-03	63E4	5	F	07	
11301	SYS	2.2 *+	27C512	U1300	160-4209-03	8F85	6	F	07	
11301	SYS	2.2 *+	27C512	U1000	160-4294-03	C437	7	F	07	
11301	SYS	2.2 *+	27C512	U1230	160-4295-03	73EB	8	F	07	
1502B	SYS	5.02*+	27C512	U2020	160-4412-09	EEC7	1	A	08	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
1502B	SYS	5.00*+	27C512	U2020	160-4413-06	8FAC	1	B	08	
1502B	SYS	5.00*+	27C512	U2020	160-4411-03	46C7	1	C	08	OPT 6
370	SYS	3.05*+	27256	U600	160-3910-05	2DBE	1	D	08	
370	SYS	3.05*+	27256	U610	160-3911-05	DADE	2	D	08	
370	SYS	3.05*+	27256	U620	160-3912-05	BFA6	3	D	08	
370	SYS	3.05*+	27256	U630	160-3913-05	CC93	4	D	08	
7D20	SYS1	1.03	2764	U500	160-1162-03	38ED	1	E1	08	
7D20	SYS1	1.03	2764	U700	160-1757-03	A0C4	2	E1	08	
7D20	SYS2	1.02	2764	U400	160-1163-02	5B2A	1	E2	08	
7D20	SYS2	1.02	2764	U200	160-1164-02	154E	2	E2	08	
7D20	SYS2	1.02	2764	U300	160-1165-02	ED91	3	E2	08	
7D20	SYS2	1.02	2764	U600	160-1676-02	0FC0	4	E2	08	
7854	SYS		2716	U400	160-0466-02	A125	1	F	08	
7854	SYS		2716	U410	160-0467-02	A0F9	2	F	08	
7854	SYS		2764	U100	160-0408-01	D34B	1	F1	08	Board mod needed or adapter must be used
7854	SYS		2764	U110	160-0409-01	65F7	2	F1	08	Board mod needed or adapter must be used
7854	SYS		2764	U200	160-0410-01	3CAE	3	F1	08	Board mod needed or adapter must be used
7854	SYS		2764	U210	160-0411-01	5F38	4	F1	08	Board mod needed or adapter must be used
834	SYS		2732		160-0836-05	7D38	1	G	08	
836	Z8		27128A		160-3182-04	6523	1	H1	08	
836	CS		27256		160-3352-07	117D	1	H2	08	
PEP301	BIOS		27128A	U41	160-V 2.00	C000	1	I	08	
PEP301	BIOS		27128A	U43	160-V 2.00	E500	2	I	08	
PEP301	BIOS		27128	U41	160-V 2.20T	4A00	1	J	08	
PEP301	BIOS		27128	U43	160-V 2.20T	3900	2	J	08	
PM104	SYS		2716		160-0835-00	ED63	1	K	08	
760		STD	2764A	U127	160-4232-00	0DE9	1	L	08	
760		STD	2764A	U137	160-4233-00	FADC	2	L	08	
760		F10	2764A	U127	160-6134-00	F2A9	1	M	08	
760		F10	2764A	U137	160-6135-00	1B30	2	M	08	
286	BIOS	AMI	27256	LO		0850	1	N	08	
286	BIOS	AMI	27256	HI		15C9	2	N	08	
1502C	SYS	5.02	27C512	U1014	160-4983-01	03A4	1	O	08	
1502C	SYS	5.04	27C512	U2020	160-9010-00	EE9C	1	P	08	B020000 - up
5223	SYS		2732	U600	160-0731-01	24F0	1	Q	08	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
5223	SYS		2732	U620	160-1026-01	C88B	2	Q	08	
TDS520										Use TDS540
TDS540	BOOT	1.5	27C010	U1331	160-8505-00	B23D	1	R	08	
TDS210										Use TDS220
TDS220	SYS	1.19	27C040		163-0792-06	FBC5	1	S	08	
TDS2CM		1.04	27C010	U206	163-0846-02	C928	1	T	08	
TDS2MM		1.02	27C040	U206	163-0986-01	979C	1	U	08	
TDS Color	Display	2.0	27C64A-20		160-9137-02	3792	1	W	08	Use in conjunction with mechanical mods, same as -00 faster chip ?
TDS Color	Display	1.0	27C64-250		160-9137-00	3792	1	V	08	
TDS220	SYS	1.17	27C040		163-0792-04	3BE6	1	X	08	
TDS220	SYS	1.18	27C040		163-0792-05	E6E9	1	Y	08	
1502C	SYS	5.04	27C512	U2002	160-8999-00	B1C7	1	Z	08	B020000 - up, System language German
TSG-300	SYS	3.5	27512	U884	160-4870-03	3A6A	1	A	09	
TSG-300	VTIM	3.5	27256	U574	160-3720-03	D7A0	1	B	09	
TSG-300	SEL	3.5	27256	U562	160-4869-02	99B0	2	B	09	
TSG-300	WFM1	3.5	27C128	U335	160-4871-06	855C	1	C1	09	
TSG-300	WFM1	3.5	27C128	U340	160-4872-06	889B	2	C1	09	
TSG-300	WFM1	3.5	27C128	U345	160-4873-06	B0CC	3	C1	09	
TSG-300	WFM1	3.5	27C128	U351	160-4874-06	C3CD	4	C1	09	
TSG-300	WFM1	3.5	27C128	U535	160-4875-06	5B74	5	C1	09	
TSG-300	WFM1	3.5	27C128	U540	160-4876-06	57AB	6	C1	09	
TSG-300	WFM1	3.5	27C128	U545	160-4877-06	4DEE	7	C1	09	
TSG-300	WFM1	3.5	27C128	U551	160-4878-06	4FC1	8	C1	09	
TSG-300	WFM2	3.5	27C128	U635	160-4879-04	650E	1	C2	09	
TSG-300	WFM2	3.5	27C128	U640	160-4880-04	6E75	2	C2	09	
TSG-300	WFM2	3.5	27C128	U645	160-4881-04	63B0	3	C2	09	
TSG-300	WFM2	3.5	27C128	U651	160-4882-04	5AE2	4	C2	09	
TSG-300	WFM2	3.5	27C128	U835	160-4883-04	6575	5	C2	09	
TSG-300	WFM2	3.5	27C128	U840	160-4884-04	664A	6	C2	09	
TSG-300	WFM2	3.5	27C128	U845	160-4885-04	6583	7	C2	09	
TSG-300	WFM2	3.5	27C128	U851	160-4886-04	66B2	8	C2	09	
WFM-300			27C64	U268	160-4196-03	9F11	1	D	09	
VM700A	BOOT		27C512		160-7282-05	A955	1	E	09	
4041	A2 CPU	2.1	MCM68766	U179	160-1241-03	849F	1	F1	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U279	160-1245-03	8CCC	1	F2	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U177	160-1248-03	EBFA	1	F3	09	Can not be burned with Elan 5000

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
4041	A2 CPU	2.1	MCM68766	U277	160-1249-03	D7BA	1	F4	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U161	160-1250-03	D0DE	1	F5	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U165	160-1251-03	C57E	1	F6	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U171	160-1252-03	437D	1	F7	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U175	160-1253-03	D3A1	1	F8	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U261	160-1254-03	1296	1	F9	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U265	160-1255-03	FB1D	1	F10	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U271	160-1256-03	FCEF	1	F11	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	MCM68766	U275	160-1257-03	54CE	1	F12	09	Can not be burned with Elan 5000
4041	A2 CPU	2.1	2716	U155	160-1621-02	624B	1	F13	09	
4041	A2 CPU	2.1	2716	U255	160-1622-02	149A	2	F13	09	
4041	F/P		2716	U185	160-1244-00	2D21	1	F14	09	
4041	A9 I/O	2.1	2732	U165	160-1242-02	A2B6	1	F15	09	
4041	A9 I/O	2.1	2732	U173	160-1243-02	6791	2	F15	09	
11801										Use 11801A
11801B										Use 11801A
CSA803										Use 11801A
CSA803A										Use 11801A
CSA803C										Use 11801C
11802	A5 TB	9.12	27512	U400	160-5580-04	7E79	1	A1	10	050-2538-03
11802	A5 TB	9.12	27512	U310	160-5581-04	CDC4	2	A1	10	
11802	A5 TB	9.12	27512	U410	160-5582-04	5632	3	A1	10	
11802	A5 TB	9.12	27512	U300	160-5632-04	3DCB	4	A1	10	
11802	A7 DSP	9.00	27512	U602	160-5502-02	1C34	1	A2	10	
11802	A7 DSP	9.00	27512	U612	160-5503-02	13D4	2	A2	10	
11802	A17 MN	9.02	27512	U240	160-5490-03	BCB7	3	A2	10	
11802	A17 MN	9.02	27512	U250	160-5491-03	1223	4	A2	10	
11802	A18 MN	9.02	27512	U630	160-5473-03	DA6B	1	A3	10	
11802	A18 MN	9.02	27512	U730	160-5474-03	5D30	2	A3	10	
11802	A18 MN	9.02	27512	U620	160-5475-03	163E	3	A3	10	
11802	A18 MN	9.02	27512	U720	160-5476-03	B6D9	4	A3	10	
11802	A18 MN	9.02	27512	U612	160-5477-03	76BD	5	A3	10	
11802	A18 MN	9.02	27512	U712	160-5478-03	78B0	6	A3	10	
11802	A18 MN	9.02	27512	U600	160-5479-03	83BD	7	A3	10	
11802	A18 MN	9.02	27512	U700	160-5619-03	2977	8	A3	10	
11802	A29 MN	9.02	27512	U210	160-5420-03	85EA	1	A4	10	
11802	A29 MN	9.02	27512	U220	160-5421-03	3093	2	A4	10	
11802	A29 MN	9.02	27512	U230	160-6515-03	32C4	3	A4	10	
11802	A29 MN	9.02	27512	U240	160-6516-03	7990	4	A4	10	
11802	A28 ACQ	9.00	27512	U611	160-4288-03	D1C7	1	A5	10	
11801A	A15 DSP	3.00	27C512	U140	160-6976-01	56C2	1	B1	10	CSAF01, 040-1323-02
11801A	A15 DSP	3.00	27C512	U150	160-6977-01	EAD4	2	B1	10	
11801A	A18 MN	3.01	27C010	U930	160-6978-03	2861	1	B2	10	
11801A	A18 MN	3.01	27C010	U830	160-6979-03	F2BE	2	B2	10	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
11801A	A18 MN	3.01	27C010	U820	160-6984-03	60C5	3	B2	10	
11801A	A18 MN	3.01	27C010	U920	160-6985-03	A0B1	4	B2	10	
11801A	A18 MN	3.01	27C010	U810	160-6986-03	1A52	1	B3	10	
11801A	A18 MN	3.01	27C010	U910	160-6987-03	E4CF	2	B3	10	
11801A	A18 MN	3.01	27C010	U800	160-6988-03	272D	3	B3	10	
11801A	A18 MN	3.01	27C010	U900	160-6989-03	9045	4	B3	10	
11801A	A5 TB	3.00	27C512	U400	160-6980-01	F01D	1	B4	10	
11801A	A5 TB	3.00	27C512	U310	160-6981-01	4770	2	B4	10	
11801A	A5 TB	3.00	27C512	U410	160-6982-01	E1E6	3	B4	10	
11801A	A5 TB	3.00	27C512	U300	160-6983-01	5CFA	4	B4	10	
11801A	A28 ACQ	9.02	27C512	U611	160-4288-05	3891	1	B5	10	
11801A	A15 DSP	4.00-	27C512	U140	160-6976-02	DBBC	1	C1	10	1180F01, 040-1425-00; CSAF01, 040-1323-03 In CSA 2 ea S-RAM's, A18U220 and A18U520, must be replaced to 156-3479-00 = 66204L
11801A	A15 DSP	4.00-	27C512	U150	160-6977-02	B063	2	C1	10	
11801A	A18 MN	4.03-	27C010	U930	160-6978-06	2205	1	C2	10	
11801A	A18 MN	4.03-	27C010	U830	160-6979-06	1FE9	2	C2	10	
11801A	A18 MN	4.03-	27C010	U820	160-6984-06	1F08	3	C2	10	
11801A	A18 MN	4.03-	27C010	U920	160-6985-06	97C2	4	C2	10	
11801A	A18 MN	4.03-	27C010	U810	160-6986-06	29E7	1	C3	10	
11801A	A18 MN	4.03-	27C010	U910	160-6987-06	C4E9	2	C3	10	
11801A	A18 MN	4.03-	27C010	U800	160-6988-06	27B3	3	C3	10	
11801A	A18 MN	4.03-	27C010	U900	160-6989-06	C6E8	4	C3	10	
11801A	A5 TB	4.01-	27C512	U400	160-6980-02	1808	1	C4	10	
11801A	A5 TB	4.01-	27C512	U310	160-6981-02	4481	2	C4	10	
11801A	A5 TB	4.01-	27C512	U410	160-6982-02	1221	3	C4	10	
11801A	A5 TB	4.01-	27C512	U300	160-6983-02	6121	4	C4	10	
11801A	A28 ACQ	9.02	27C512	U611	160-4288-05	3891	1	B5	10	
11801A	A15 DSP	4.00-	27C512	U140	160-6976-02	DBBC	1	C1	10	1180F01, 040-1425-01; CSAF01, 040-1323-04 In CSA 2 ea S-RAM's, A18U220 and A18U520, must be replaced to 156-3479-00 = 66204L
11801A	A15 DSP	4.00-	27C512	U150	160-6977-02	B063	2	C1	10	
11801A	A18 MN	4.04-	27C010	U930	160-6978-07	3088	1	D1	10	
11801A	A18 MN	4.04-	27C010	U830	160-6979-07	EB19	2	D1	10	
11801A	A18 MN	4.04-	27C010	U820	160-6984-07	F926	3	D1	10	
11801A	A18 MN	4.04-	27C010	U920	160-6985-07	38EA	4	D1	10	
11801A	A18 MN	4.04-	27C010	U810	160-6986-07	F1CC	1	D2	10	
11801A	A18 MN	4.04-	27C010	U910	160-6987-07	78A0	2	D2	10	
11801A	A18 MN	4.04-	27C010	U800	160-6988-07	154B	3	D2	10	
11801A	A18 MN	4.04-	27C010	U900	160-6989-07	B332	4	D2	10	
11801A	A5 TB	4.03-	27C512	U400	160-6980-02	1808	1	D3	10	
11801A	A5 TB	4.03-	27C512	U310	160-6981-03	D6F5	2	D3	10	
11801A	A5 TB	4.03-	27C512	U410	160-6982-02	1221	3	D3	10	
11801A	A5 TB	4.03-	27C512	U300	160-6983-03	DE21	4	D3	10	
11801A	A28 ACQ	9.02	27C512	U611	160-4288-05	3891	1	B5	10	
11802	A5 TB	8.52	27512	U400	160-5580-02	06DF	1	E1	10	
11802	A5 TB	8.52	27512	U310	160-5581-02	6BF3	2	E1	10	
11802	A5 TB	8.52	27512	U410	160-5582-02	FE3C	3	E1	10	
11802	A5 TB	8.52	27512	U300	160-5632-02	1858	4	E1	10	
11802	A7 DSP	8.05	27512	U602	160-5502-01	1C4D	1	E2	10	
11802	A7 DSP	8.05	27512	U612	160-5503-01	13D4	2	E2	10	
11802	A17 MN	8.20	27512	U240	160-5490-02	7EC3	3	E2	10	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
11802	A17 MN	8.20	27512	U250	160-5491-02	D2C2	4	E2	10	
11802	A18 MN	8.20	27512	U630	160-5473-02	E56C	1	E3	10	
11802	A18 MN	8.20	27512	U730	160-5474-02	616B	2	E3	10	
11802	A18 MN	8.20	27512	U620	160-5475-02	1738	3	E3	10	
11802	A18 MN	8.20	27512	U720	160-5476-02	BC32	4	E3	10	
11802	A18 MN	8.20	27512	U612	160-5477-02	7AC1	5	E3	10	
11802	A18 MN	8.20	27512	U712	160-5478-02	7FA4	6	E3	10	
11802	A18 MN	8.20	27512	U600	160-5479-02	1FBC	7	E3	10	
11802	A18 MN	8.20	27512	U700	160-5619-02	ABC8	8	E3	10	
11802	A29 MN	8.20	27512	U210	160-5420-02	9359	1	E4	10	
11802	A29 MN	8.20	27512	U220	160-5421-02	3A8C	2	E4	10	
11802	A29 MN	8.20	27512	U230	160-6515-00	39F9	3	E4	10	
11802	A29 MN	8.20	27512	U240	160-6516-00	8095	4	E4	10	
11802	A28 ACQ	8.01	27512	U611	160-4288-02	D071	1	E5	10	
11801C	A15 DSP	4.00-	27C512	U140	160-6976-02	DBBC	1	C1	10	Upgrade from 11801B (118CFC) or CSA803A (CSA8FC): A18U440 to 163-0999-00 plus several other hardware upgrades Must have Acq unit 657-0059-02 or higher and T/B board 670-9362-53 or higher (included in 040-1329-00)
11801C	A15 DSP	4.00	27C512	U150	160-6977-02	B063	2	C1	10	
11801C	A18 MN	4.05	27C010	U930	160-6978-08	E3BA	1	F1	10	
11801C	A18 MN	4.05	27C010	U830	160-6979-08	ECFC	2	F1	10	
11801C	A18 MN	4.05	27C010	U820	160-6984-08	E36F	3	F1	10	
11801C	A18 MN	4.05	27C010	U920	160-6985-08	B0AB	4	F1	10	
11801C	A18 MN	4.05	27C010	U810	160-6986-08	A847	1	F2	10	
11801C	A18 MN	4.05	27C010	U910	160-6987-08	5829	2	F2	10	
11801C	A18 MN	4.05	27C010	U800	160-6988-08	0A1E	3	F2	10	
11801C	A18 MN	4.05	27C010	U900	160-6989-08	B3CF	4	F2	10	
11801C	A5 TB	4.03	27C512	U400	160-6980-02	1808	1	D3	10	
11801C	A5 TB	4.03	27C512	U310	160-6981-03	D6F5	2	D3	10	
11801C	A5 TB	4.03	27C512	U410	160-6982-02	1221	3	D3	10	
11801C	A5 TB	4.03	27C512	U300	160-6983-03	DE21	4	D3	10	
11801C	A28 ACQ	9.02	27C512	U611	160-4288-05	3891	1	B5	10	
DSA602										Use DSA601A
DSA602A										Use DSA601A
DSA601	A18	1.3+	27C010	U800	160-4918-03	7395	1	A1	11	
DSA601	A18	1.3+	27C010	U810	160-4919-03	9ADB	2	A1	11	
DSA601	A18	1.3+	27C010	U820	160-4920-03	E1F9	3	A1	11	
DSA601	A18	1.3+	27C010	U830	160-4921-03	8B53	4	A1	11	
DSA601	A18	1.3+	27C010	U900	160-4922-03	75DB	5	A1	11	
DSA601	A18	1.3+	27C010	U910	160-4923-03	A517	6	A1	11	
DSA601	A18	1.3+	27C010	U920	160-4924-03	FF4B	7	A1	11	
DSA601	A18	1.3+	27C010	U930	160-4925-03	1B3F	8	A1	11	
DSA601	A16	1.3+	27C512	U440	160-4782-03	2814	1	A2	11	
DSA601	A16	1.3+	27C512	U540	160-4783-03	5F77	2	A2	11	
DSA601	A17	1.3+	27C512	U240	160-5469-03	B9F0	3	A2	11	
DSA601	A17	1.3+	27C512	U250	160-5470-03	52C4	4	A2	11	
DSA601	A19	1.31+	27C512	U410	160-4784-04	02A0	1	A3	11	
DSA601	A19	1.31+	27C512	U510	160-4785-04	CEA9	2	A3	11	
DSA601	A19	1.31+	27C512	U420	160-4786-04	2864	3	A3	11	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
DSA601	A19	1.31+	27C512	U520	160-4787-04	E734	4	A3	11	
DSA601	A19	1.31+	27C256	U460	160-5955-04	A2D8	1	A4	11	
DSA601	A19	1.31+	27C256	U560	160-5956-04	8A36	2	A4	11	
DSA601A	A18	2.23+	27C010	U800	160-4918-07	8C69	1	B1	11	
DSA601A	A18	2.23+	27C010	U810	160-4919-07	E193	2	B1	11	
DSA601A	A18	2.23+	27C010	U820	160-4920-07	5DF6	3	B1	11	
DSA601A	A18	2.23+	27C010	U830	160-4921-07	B338	4	B1	11	
DSA601A	A18	2.23+	27C010	U900	160-4922-07	F966	5	B1	11	
DSA601A	A18	2.23+	27C010	U910	160-4923-07	BDC0	6	B1	11	
DSA601A	A18	2.23+	27C010	U920	160-4924-07	DE39	7	B1	11	
DSA601A	A18	2.23+	27C010	U930	160-4925-07	DCCD	8	B1	11	
DSA601A	A16	2.2+	27C512	U440	160-4782-06	9873	1	B2	11	
DSA601A	A16	2.2+	27C512	U540	160-4783-06	E34E	2	B2	11	
DSA601A	A17	2.23+	27C512	U240	160-5469-07	54B6	3	B2	11	
DSA601A	A17	2.23+	27C512	U250	160-5470-07	F671	4	B2	11	
DSA601A	A19	2.23+	27C512	U410	160-4784-08	012E	1	B3	11	
DSA601A	A19	2.23+	27C512	U510	160-4785-08	E483	2	B3	11	
DSA601A	A19	2.23+	27C512	U420	160-4786-08	0F74	3	B3	11	
DSA601A	A19	2.23+	27C512	U520	160-4787-08	8843	4	B3	11	
DSA601A	A19	2.23+	27C256	U460	160-5955-08	A6B8	1	B4	11	
DSA601A	A19	2.23+	27C256	U560	160-5956-08	9B72	2	B4	11	
11A34										Use 11A32
11A32	SYS	3.5*	27128A	U700	160-4009-07	3532	1	M	12	
11A32	SYS	3.6	27128A	U700	160-4009-08	4EC3	1	A	12	
11A33	SYS	2.3*	27128A	U521	160-4227-03	94B9	1	I	12	
11A33	SYS	2.4*	27128A	U521	160-4227-04	91E8	1	B	12	
11A33	SYS	2.5	27128A	U521	160-4227-05	8CED	1	H	12	
11A52	SYS	3.7*	27128A	U700	160-4010-07	765B	1	L	12	
11A52	SYS	3.8	27128A	U700	160-4010-08	6741	1	C	12	
11A71	SYS	3.4*	27128A	U800	160-4065-05	5F16	1	J	12	
11A71	SYS	3.8-	27128A	U800	160-4065-08	6A18	1	D	12	
11A72	SYS	2.2	27C128	U1110	160-4845-08	F0AB	1	N	12	
11A72	SYS	2.3*+	27C128	U1110	160-4845-09	EFBF	1	E	12	
11T5H	SYS	1.2	27C256		160-7333-00	8541	1	F	12	
11A34V	SYS	4.1	27C128		160-8222-00	657E	1	G	12	

* = not latest version		+ = direct replacement of previous				- = mod required, see microfiche				
INSTRUMEN	POS	VER	DEVICE	U #	P/N	C'SUM	SOCKET	FILE	FOLDER	COMMENTS
11A16	SYS	1.3	27C128	U1080	160-6636-02	20C0	1	K	12	
Elan 5000	F/W	5.01	27C020			BA4A	1	A	13	From UK
Elan 5000	F/W	7.05	27C020			BDFE	1	B	13	Lock up, downloaded
Elan 5000	F/W	7.01	27C020			89FA	1	C	13	Lock up, from France
Elan 5000	F/W	5.07	27C020			F3C3	1	D	13	Original från Tek
2445B	NVRAM		DS1225	U	N/A	E5D8	1	E	13	From S/N B061497